



2835 MHz Cavity Bandpass Filter

Part Number: AB2835B1262

ANATECH ELECTRONICS INC
RF & Microwave Filters & Products



Electrical specifications

Center Frequency: 2835 MHz
Frequency Range: 2807~2863 MHz
Insertion Loss: ≤ 3.4 dB
Return Loss: ≥ 15 dB
Rejection: ≥ 40 dB@2775 MHz
Power: 1W

Mechanical

Mounting Method: Threaded Mounting
Connector Type: SMA(F)
Dimensions: 4.00" x 1.25" x 0.75" in
Surface Finish: Black

Environmental

Operating Temperature: -40°C to +85°C
Operating Humidity: $\leq 95\%$ RH

Outline Drawing:

